



1. SEE SHEET E001 FOR SYMBOLS, ABBREVIATIONS AND LIGHTING FIXTURE SCHEDULE.
2. ALL EXISTING RECEPTACLES AND OTHER EQUIPMENT NOT SHOWN SHALL BE KEPT IN USE UNLESS SPECIFICALLY NOTED OTHERWISE. RECONNECT BRANCH CIRCUITS SERVING RESPECTIVE AREA SERVED BY NEW PANEL THAT REPLACES OLD SINGLE PHASE PANEL. VERIFY EXISTING CONDITIONS ON SITE.
3. NEW CIRCUIT NUMBERS INDICATED ARE NOT NECESSARILY ACTUAL NUMBERS IN PANEL, BUT ARE SHOWN TO DETERMINE QUANTITIES, SIZES ETC. VERIFY ACTUAL NUMBERS IN PANEL ON SITE. COORDINATE WITH CIRCUITS SERVING EXISTING EQUIPMENT.

- 1 LOCATE ON ROOF
- 2 ALL RECEPTACLES IN KITCHEN B7 INDICATED WITH TWO CIRCUITS TO BE SPLIT WIRED WITH ONE CIRCUIT TO TOP RECEPTACLE AND SECOND CIRCUIT TO BOTTOM RECEPTACLE.
- 3 FAN TO BE CONTROLLED VIA LIGHTING OCCUPANCY SENSOR. ROOM SWITCH ("B" DESIGNATION) SERVES AS LOCAL OVERRIDE, FIX OCCUPANCY SENSOR TIME DELAY TO 15 MINUTES
- 4 120V POWER FOR EXHAUST HOOD LIGHTS
- 5 RECEPTACLE FOR PORTABLE GENERATOR
- 6 PROVIDE DEDICATED 120 VOLT, 20 AMP CIRCUIT FOR EACH RECEPTACLE DESIGNATED WITH "D"
- 7 PROVIDE (1) 2" CONDUIT FROM WATCH ROOM NEAR ALERTING CABINET TO ROOF ABOVE FOR TWO ANTENNA CABLES.
- 8 PROVIDE CONNECTION FOR FOOD WASTE DISPOSER. SEE EQUIPMENT SCHEDULE ON SHEET E001 FOR SPECIFICATIONS.
- 9 PROVIDE CONNECTION AND WIRING FOR MEGHO SHADES. SEE ARCHITECTURAL FOR EXACT LOCATION AND INFORMATION.
- 10 PROVIDE RECEPTACLE MOUNTED 60" ABOVE FINISHED FLOOR FOR MICROWAVE CUPNET AREA. SEE ARCHITECTURAL FOR EXACT LOCATION.

| | |
|---------------|----------|
| DRAWN | KK |
| CHECKED | AS |
| DATE | 03-09-12 |
| PROJECT NO. | 2011009 |
| PROJECT TITLE | |

421 GRAND CANYON DRIVE
MADISON, WISCONSIN

SHEET NO.
E201P